SUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.com





## Outside dimensions



Note: Usage warning: The wire may stop midway through retracting. When this happens, slowly pull out the full length and then slowly retract again before using.

## Output circuit diagram



A capacitor (0.1 $\mu$ F) is connected between 0V and FG (frame ground).

## Output waveform



## Specifications/linear scale encoder (detection portion)

Type name	MLS-3	30-	500		
	Pulse number = No entry=voltage output •C=open collector output •C=copen collector output •C=copen collector output DC24V				
Item	MLS- 30-450-500	MLS- 30-450-1000		MLS- 30-4500-1000	
Measuring range mm	500	1,000	500	1,000	
Output pulse/1mm	5	5	50	50	
Stroke speed mm/sec	1,000	1,000	1,000	1,000	
Absolute accuracy mm	±0.25	±0.5	±0.25	±0.5	
Minimum resolution mm	0.2	0.2	0.02	0.02	
Supply voltage		2V±10% 10%(option)	DC5~12V±10% DC24V±10%(option)		
Current consumption	60mA or less (under no load)				
Output phase	A phase, B phase				
Output form	Square wave				
Output capacity	Sink current 20mA or less, residual voltage 0.5V or less (at 10mA)				
Response frequency	100kHz				
Output phase	A, B phase difference 90°±45°				
Waveform rise/fall time	2µsec or less				
Wire tensile force	1.4N~2.9N(150~300gf)				
Working ambient temperature/humidity	0℃~50℃/RH35%~90%				
Storage ambient temperature	−20~80°C				
Vibration resistance	Endurance 10 to 55Hz Double amplitude 2 hours each in X, Y, and Z directions				
Impact resistance	Durability 500m/s <sup>2</sup> (about 50G) 3 times each in X, Y, and Z directions				
Cable	Insulated shield wire Outside diameter $\phi$ 4.2 4-core vinyl wire				
Mass	185g				
Note: The output pulse or resolution is possible to 4 multiple with the counter.					

Specifications/micro linear scale (detecting portion + indicating portion)						
Type name	MLS- 30-01-500	MLS- 30-01-1000	MLS- 30-001-500	MLS- 30-001-1000		
Measuring range mm	500	1,000	500	1,000		
Output pulse/1mm	10	10	100	100		
Counter accuracy pulse	±1	±1	±1	±1		
Minimum reading	0.1	0.1	0.01	0.01		
Power	AC100V 50/60Hz 180mA max					
Counter mode	10 Decimal					
Count indication	0~±999999.9		0~±99999.99			
Reset	Reset switch provided *External signal resetting possible					
External output	*BCD parallel output					
Mass	700g					
Power cord	2m with plug					

Note: For counter specifications, see DC Series. \* indicates option.