SUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.com







## Specifications

Specifications								
Type name			REH-30- R Pulse number Output circuit •No entry=voltage output •C = open collector output •C4					
item			DC5~12V ±10%					
Supply voltage			DC24V±10%(open collector output only)					
Current consumption			60mA or less (under no load)					
Detection system			Incremental					
	Output pulse number		200	400	500	1,000	2,000	
Output	Output pulse/1mm		1	2	2.5	5	10	
	Minimum resolution mm		1	0.5	0.4	0.2	0.1	
	Output phase		A, B, Z phase					
	Output form		Square wave					
	Output capacity		Sink current: 20mA Residual voltage: 0.5V or less (at 10mA)					
	Maximum response frequency (response pulse number)		100kHz					
	Output phase difference		A, B phase difference $90^{\circ}\pm45^{\circ}(T/4\pm T/8)$ Z phase T±T/2 (see Output Waveform)					
	Waveform rise/fall time		2µs or less (output cable 1m or less)					
	Allowable load of	Radial	19.6N(2kgf) 14.7N(1.5k			(1.5kgf)		
shaft (electrical)		Thrust	9.8N(1kgf) 4.9N		4.9N(	0.5kgf)		
Maximum allowable revolutions (mechanical)			6,000r/min					
Roller			Outside diameter: $\phi$ 63.68±0.01 Material: aluminum roll hard urethane rubber baked					
Working ambient temperature/ humidity			0℃~60℃ RH35%~90% no dewing					
Storing ambient temperature			−20°C~80°C					
Vibration resistance			Durability 55Hz, double amplitude 1.5mm 2 hours each in X, Y, and Z directions					
Impact resistance			Durability 500m/s <sup>2</sup> (about 50G) 3 times each in X, Y, and Z directions					
Cable			Outside diameter $\phi$ 4.2 5-core vinyl wire Insulated shield cable (length 1m)					
Mass			400g					



A capacitor (0.1 $\mu$ F) is connected between 0V and FG (frame ground).

## Output waveform

