# **PT9DN** Heavy Industrial • DeviceNET®

Linear Position/Velocity to 550 inches (1400 cm) Aluminum or Stainless Steel Enclosure Options VLS Option To Prevent Free-Release Damage IP67 • NEMA 6 Protection

## GENERAL

Full Stroke Range Options (on this datasheet)		0-75 to 0-550 inches	
Electrical Signal Interface		CANbus ISO 11898	
Protocol		DeviceNET Version 2.0	
Accuracy		$\pm$ 0.10% full stroke	
Repeatability		± 0.02% full stroke	
Resolution		$\pm$ 0.003% full stroke	
Measuring Cable Options	nylon-coated stair	nless steel or thermoplastic	
Enclosure Material	powder-painted a	aluminum or stainless steel	
Sensor	plastic-hybr	id precision potentiometer	
Potentiometer Cycle Life		≥ 250,000 cycles	
Maximum Retraction Acceleration		see ordering information	
Maximum Velocity		see ordering information	
Weight, Aluminum (Stainless Steel) Enclosure		8 lbs. (16 lbs.), max.	

### ELECTRICAL

Input Voltage	bus powered		
Input Current	40 mA max.		
Address Setting/Node ID	063 set via DIP switches (default: 63)		
Baud Rate	125K, 250K or 500K set via DIP switches		
EDS File	available @ http://celesco.com/downloads		
ENVIRONMENTAL			

Enclosure	NEMA 4/4X/6, IP 67
Operating Temperature	-40° to 200°F (-40° to 90°C)
Vibration	up to 10 g to 2000 Hz maximum





The PT9DN communicates via DeviceNET protocol with programmable controllers in factories and harsh environments requiring linear position measurements in ranges up to 550".

As a member of Celesco's innovative family of NEMA 4 rated cable-extension transducers, the PT9DN installs in minutes by simply mounting it's body to a fixed surface and attaching it's cable to the movable object. Perfect parallel alignment not required.

### Output Signal:



20630 Plummer Street 
 Chatsworth, CA 91311
tel: 800.423.5483 
 +1.818.701.2750 
 fax: +1.818.701.2799

measurement

celesco.com • info@celesco.com

SUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.com<sub>PT9DN</sub> | 1

#### I/O Format:



#### \*Current Measurement Count

The **C**urrent Measurement **C**ount (**CMC**) is the output data that indicates the present position of the measuring cable.

The CMC is a 16-bit value that occupies the first two bytes ( $B_0$  and  $B_1$ ) of the data field.  $B_0$  is the LSB (least significant byte) and  $B_1$  is the MSB (most significant byte).

The CMC starts at 0000H with the measuring cable fully retracted and continues upward to the end of the stroke range stopping at FFFFH. This holds true for all ranges.

#### \*\*Full Stroke Range

The Full Stroke Range (FSR) is a 16-bit value in the data field that expresses the full range of the sensor in inches. This value can be used to convert the actual count to units of measurement should the application require it.

The full stroke measurement range occupies the second two bytes  $(B_2 \text{ and } B_3)$  of the data field.

 $\rm B_2$  is the LSB (least significant byte) and  $\rm B_3$  is the MSB (most significant byte).

This value is expressed in inches.

#### Example:

Hex Value	Decimal Equivalent	Full Stroke Range	
001E	30	30 inches	

#### **Converting CMC to Inches**

If required, the CMC can easily be converted to a linear measurement expressed in inches instead of just counts.

This is accomplished by first dividing the CMC by 65,535 (total counts over the range) and then multiplying that value by the FSR:

$$\left( \frac{CMC}{65,535} \right) X$$
 FSR

Example:

If the full stroke range is **30 inches** and the current position is **OFF2 Hex** (4082 Decimal) then,

$$\left( \frac{4082}{65,535} \right) X$$
 30.00 inches = 1.87 inches

#### Address Setting (Node ID), Baud Rate and Bus Termination Settings

#### Address Setting (Node ID)

The Address Setting (Node ID) is set via 6 switches located on the 8-pole DIP switch found on the DeviceNET controller board located inside the transducer.

The DIP switch settings are binary starting with switch number  $1 (= 2^0)$  and ending with switch number  $6 (= 2^5)$ .

<b>DIP-1</b> (2 <sup>0</sup> )	<b>DIP-2</b> (2 <sup>1</sup> )	<b>DIP-3</b> (2 <sup>2</sup> )	<b>DIP-4</b> (2 <sup>3</sup> )	<b>DIP-5</b> (2 <sup>4</sup> )	<b>DIP-6</b> (2 <sup>5</sup> )	<i>address</i> (decimal)
0	0	0	0	0	0	0
1	0	0	0	0	0	1
0	1	0	0	0	0	2
1	1	1	1	1	1	63



#### DeviceNET Controller Board and DIP Switch Location



#### Baud Rate

The transmission baud rate may be either factory preset at the time of order or set manually at the time of installation.

The baud rate can be set using switches **7** & **8** on the 8-pole DIP switch found on the DeviceNET controller board located inside the transducer.



#### **Bus Termination**

The setting of the internal bus termination resistor may be specified upon order or manually changed by the end user at the time of installation.

The bus termination resistor is activated setting switches 1 & 2 on the 2-pole DIP switch (located on the internal DeviceNET controller board) to the "ON" position.



Caution! Do Not Remove Spring-Side End Cover removing spring-side end cover could cause spring to become unseated and permanently damaged.

# <u>celesco</u>

celesco.com • info@celesco.com

tel: 800.423.5483 • +1.818.701.2750 • fax: +1.818.701.2799

now part of Measurement Specialties, Inc.

2 | PT9DNSUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.com



Fig. 1 – Outline Drawing (18 oz. cable tension only)

# VLS Option - Free Release Protection

The patented Celesco Velocity Limiting System (VLS) is an option for PT9000 Series cable extension transducers that limits cable retraction to a safe 40 to 55 inches per second for the single spring option and 40 to 80 inches per second for the higher tension dual spring option.

The VLS option prevents the measuring cable from ever reaching a damaging velocity during an accidental free release. This option is ideal for mobile applications that require frequent cable disconnection and reconnection. It prevents expensive unscheduled downtime due to accidental cable mishandling or attachment failure.

How To Configure Model Number for VLS Option:



tel: 800.423.5483 • +1.818.701.2750 • fax: +1.818.701.2799

now part of Measurement Specialties, Inc.

celesco celesco.com • info@celesco.com

0.37

0.49

0.73

0.98

1.22

1.47

1.71

1.96

n/a

n/a

n/a

Ordering Information:



celesco.com • info@celesco.com

tel: 800.423.5483 • +1.818.701.2750 • fax: +1.818.701.2799

now part of Measurement Specialties, Inc.

PT9DNSUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.com 4

Ordering Information (cont.):

# Terminating Resistor:



# VLS Option - Free Release Protection

The patented Celesco Velocity Limiting System (VLS) is an option for PT9000 Series cable extension transducers that limits cable retraction to a safe 40 to 55 inches per second for the single spring option and 40 to 80 inches per second for the higher tension dual spring option.

The VLS option prevents the measuring cable from ever reaching a damaging velocity during an accidental free release. This option is ideal for mobile applications that require frequent cable disconnection and reconnection. It prevents expensive unscheduled downtime due to accidental cable mishandling or attachment failure. How To Configure Model Number for VLS Option:



tel: 800.423.5483 • +1.818.701.2750 • fax: +1.818.701.2799

now part of Measurement Specialties, Inc.

celesco.com • info@celesco.com



Fig. 2 – Outline Drawing (36 oz. cable tension only)

DIMENSIONS ARE IN INCHES [MM] tolerances are 0.03 IN. [0.5 MM] unless otherwise noted.

celesco

celesco.com • info@celesco.com



#### MEASURING CABLE RANGE Ø.031 in. Ø.034 in. Ø.047 in. Ø.062 in. 75 0.22 0.29 0.37 n/a 100 0.29 0.39 0.49 n/a 150 0.59 0.73 n/a 0.44 200 n/a 0.58 0.79 0.98 250 0.73 0.98 1.22 n/a 300 n/a 0.88 1.18 1.47 350 1.02 1.38 1.71 n/a 1.17 1.57 400 1.96 n/a 450 1.31 1.77 n/a n/a 500 n/a 1.46 1.97 n/a 550



\* tolerance = +.005 -.001 [+.13 -.03] \*\* tolerance = +.005 -.005 [+.13 -.13]

version: 8.0 last updated: August 15, 2013

tel: 800.423.5483 • +1.818.701.2750 • fax: +1.818.701.2799

now part of Measurement Specialties, Inc.