



Applications

Advantages

- Zero point detection
- Wide range of application
- Aligning and level control
 Angle
- Low vibration sensitivity
 Low price
- 5

Pinout



1	+Ub	Supply Voltage
2	GND	Ground
3	Erde	Earth
4	GNDx	Ground for analog output lx
5	GNDy	Ground for analog output ly
6	lx	Current output Ix
7	ly	Current output ly





NS-5/V2I Dual Axis Inclinometer

With current output

The NS-5/V2I dual-axis inclinometer is a member of a family of high performance, competitively priced, single and dual-axis inclinometers. The heart of every HL Planartechnik inclinometer is a small, state-of-the-art, inclination sensor. The sensor, which is comprised of a molded, ceramic case bonded, via a glass sealing process, to a ceramic substrate. Thin film, platinum electrodes are deposited on the substrate. Then the chamber is partially filled with electrolytic fluid and hermetically sealed. The molded, ceramic, sensor housing combined with a precise, planar electrode geometry yields excellent performance and consistent part-to-part uniformity.

All VI-type inclinometers have an internal pre-processor and produce a 4-20 mA current output. They have a compact sturdy design and a whole range of uses are possible thanks to the possibility of many different externalswitching combinations. With their machined, aluminum baseplate and IP 65 housing, they are an ideal choice for a variety of industrial, automotive and aerospace applications.

Diagram (angle vs. output signal)



Specifications

Range:	±5°
Precision:	0.03° for -3° +3°
Resolution:	0.001°
Temperature stability:	
Zero point:	0.1° for 0°C 50°C
Sensitivity:	0.3° for 0°C 50°C
Analog Output:	≈ 20mA (-5°) to
	<i>≈ 4mA (</i> +5°)
Operating temp. Range:	0°C +70°C
Storage temp. Range:	-40°C +85°C
Supply voltage:	+12+24VDC
Current consumption:	ca. 30mA
Protection class:	IP 65
Connection:	Connector or Pigtail

HL-Planartechnik GmbH Hauert 13, D - 44 227 Dortmund, Tel.: +49 (0) 231/97400, Fax.: +49 (0) 231/974020 Internet: <u>http://www.hlplanar.com</u> E-Mail: service @hlplanar.de SUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.@emd:29.06.01 Design: Zn